

Specif:



## RC2-340BF Screw Compressor

<b>;</b>	cations	Displacement	CFM 60 Hz		240		
Ц	cations	Rated Speed	Rpm	60 Hz	3550		
		Volume Ratio	Vi		2.6 (standard other Vi available)		
	Compressor	Nominal Hp			121 Hp at 60 Hz		
		Capacity Control	%		35%,50%,75% & 100% Step Capacity Control, 50%~100% Continuous Stepless Capacity Controls		
		Lubrication			Differential Pressure Feed Lubricant		
		Туре			3 Phase, 2 Pole, Squirrel Cage, Induction Motor		
	Motor	Insulation			Class F		
		Protection			3 PTC Protection 1 per winding		
	Lubricant Charge				No internal oil separator or sump		
	Hydrostatic Pressure test	lb/in <sup>2</sup> G			597		
	Weight	Pounds			1367		


## **Standard Compressors Accessories**

- Modulating Slide Capacity
- Weather Proof Terminal Box for outdoor applications
- 115/1/60 Control Voltage
- Horizonal Discharge Check Valve
- Discharge Service Valve (Discharge Stop Valve) with standard connection sizes and supplied with flanges and bushings
- Suction Service Valve (Suction Stop Valves) with standard connection sizes and supplied with flanges and bushings
- Suction Filter

- PSI Relief Valve
- Oil Sight Glass
- PT1000 for Reading Motor Temp
- INT69HBY supporting motor and discharge (PTC) temperature sensor protection as well as Phase Loss and Phase Reversal at Start Up Only

## **Ports**

- External Oil Cooler
- Liquid Injection (into screw chamber)
- Economizer



## **Connections**

Discharge Stop Valve	2 1/2"				1.4	_ C
Horizonal Discharge Check Valve	2 1/2"					
Suction Stop Valve	4"		_+_		2 *	
Economizer	7/8" solder					
Liquid Injection (chamber)	5/8" flare	Α	В	С	D	Е
Discharge Side	Copper Pipe Sizing 2 5/8"	2.36"	4.33"	1.38"	2.63"	3.03"
Suction Side	Copper Pipe Sizing 4 1/8"	2.99"	5.71"	1.97"	4.14"	4.57"

MCC	& LRA	<b>A</b>	R22, R407C, R404A, R507A, R134a						
			Maximum	Y	-Δ	Part Wind Start			
	Hertz	Volts	Continuous Current	Locked Rotor Amps (Y)	Locked Rotor Amps (D)	Locked Rotor Amps (D)	Locked Rotor Amps (DD)		
	60	220	457	662	1985	1342	2065		
	60	460	218	360	1080	640	985		