



MAG-KEYPAD-REPLACEMENT

Description & Specifications



Part # MAG-KEYPAD-REPLACEMENT
Replacement for all Non-Warranty Keypads



Description


Magnum LCD / Keypad Replacement - OEM Mount

The MAG-KEYPAD-REPLACEMENT contains the necessary parts to replace older or newer keypads. The kit contains keypad cabling with ferrites at each end to suppress noise.

The Magnum Keypad consists of: three function keys, four directions keys and two selection keys (Menu & Enter)

The display LCD is 128 x 64 dot pixel graphics, 2.8" diagonal viewing area with white characters on a dark background (reversible).

There is a RS485 port on the back of the replacement keypad. An instruction sheet is enclosed with each kit for proper installation.



Specifications

Keypad/LCD
NEMA rated Type 1

Display.....	128 x 64 dot pixel STN monochrome graphics LCD with 2.8" diagonal viewing area
Color.....	White characters on a blue background (Reversible)
Keypad Size.....	5.26"w x 8.50"h (8 mounting studs)
Keypad Layout.....	9 keys (3 function keys)
Connection.....	6 conductor shielded cable (max length of cable is 10 feet)
RS-485 Comm Port.....	1 @ 19,200 baud
Operating Temperature.....	-4°F to +158°F (-20°C to +70°C)
Operating Humidity.....	0-95% Non-Condensing
Storage Temperature.....	-22°F to +185°F (-30°C to +85°C)


Packaging

Keypad Interface Board w/RS485 port
MAG-Keypad-Cable
Install sheet

Ship Weight 1.88 lb
Box Dimensions..... 14 x 9.5 x 2.5" (approx).

Option

MCS-RS-485-EXTENDER



Revision - 2024-08-27